

BE-6500ERUSC

6500 WATT GENERATOR



85.508.009
Generator Cover



*Only for sale in USA



Specifications

Part Number: **BE-6500ERUSC**
 Displacement: **389cc Powerease Pull Start**
 Max Watt Output: **6500**
 Cont. Watt Output: **5500**
 Receptacles: **2x120V 20A GFCI**
1x120V/240V 30A Twistlock
12V DC 8.3A
7M: @ 74DB

Decible Rating: **7M: @ 74DB**

Warranty

Engine: **2 year**

Features

- Electric/recoil start
- Low Oil Shutdown
- Automatic Voltage Regulator (AVR)
- THD (Total Harmonic Distortion) 8
- Cont. AMPS (120V) 46A
- Fuel Tank Capacity: 25 L / 6.6 gal
- Run time per tank: 7hr @ full load
- 8" Wheel Kit (no flat wheels)
- Digital Multi Meter (hours, voltage, frequency)
- Fuel Gauge
- Automatic idle down
- Circuit Breakers
- 1 x 23A 240V AC Dual Pole *Manual Reset
- 2 x 20A 120V AC *Push to Reset
- 1 x 10A DC *Push to Reset

Shipping

Weight: **195 lbs**
 Dimensions (in): **28L x 23W x 23H**
 Units Per Pallet: **8**

Lynco Lynco Products Inc
 #114, 1220 - 28 STREET N.E.
 CALGARY, AB T2A 6A2
 403-250-3600 / 1-877-249-3600
 sales@lynco.pro / www.lynco.pro



BE Power Equipment | The Power You Need.

BEPOWEREQUIPMENT.COM